

STOP!

If you have any issues with the product, please contact our technical support team before returning it.

TECHNICAL SUPPORT

Technical Support : 1 (800) 881 9305
1 (714) 666 1716 X2

Email : support@ezq.com

Service Hours : Mon. - Fri. 08:00 AM - 05:00 PM P.S.T

EZQuest®

Premium Digital Life Accessories

Quick Instruction Manual for

UltimatePower 120W GaN USB-C PD Wall Charger X50120

UltimatePower 90W GaN USB-C PD Wall Charger X50090

UltimatePower 65W GaN USB-C PD Wall Charger X50065

Package Contents:

- UltimatePower Wall Charger
- 2 Meter DuraGuard USB-C Charge and Sync Cable
- EU International Converter
- Quick Setup Guide

1. Connect the UltimatePower Wall Charger to an outlet
2. Power USB-C laptops and other devices simultaneously. The UltimatePower will allocate power based on the USB-C devices need



UltimatePower Wall Charger 120W

3. Our 2 Meter DuraGuard USB-C Charge and Sync Cable is 100W with E-Mark so you can charge all your devices from 18W to 100W

Kevlar® Core with Nylon Braided and Strain Relief

Designed to withstand any twist, tug or tangle with

50,000

Bend Lifespan*



4. The UltimatePower charger also comes with an EU pin converter which makes it perfect for traveling worldwide with universal 100V - 240V voltage so you can charge in any country that uses a US or European plug



UltimatePower Wall Charger 120W

5. Fast charge compatible USB-C devices including phones, tablets and laptops
6. Use the USB-A port to power smartphones, tablets or media devices

The UltimatePower wall chargers are equipped with Intelligent Power Allocation so they adjust output based on how many and what type of devices are connected.

Here are the output specifications for each UltimatePower wall charger:

Output for UltimatePower 120W GaN USB-C PD Wall Charger Part No. X50120:

USB-C1: 3.3-20V/5A (PPS), 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A (Max 100W)

USB-C2: 3.3-20V/5A (PPS), 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A (Max 100W)

USB-A: 5V/3.5A, 9V/3A, 10V/2A, 12V/2.5A, 20V/1.5A (Max 30W)

USB-C1+USB-C2: 90W+30W/60W+60W/30W+90W (Max 120W)

USB-C1+USB-C2+USB-A: 65W+30W+18W/45W+45W+18W/30W+65W+18W (Max. 113W)



Output for UltimatePower 90W GaN USB-C PD Wall Charger Part No. X50090:

USB-C1: 3.3-11V/5A, 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V Max 4.5A (Max 90W)

USB-C2: 3.3-11V/5A, 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V Max 4.5A (Max 90W)


USB-A: 4.5V/5A, 5V/4.5A, 9V/3A, /12V/3A, 20V/3A (Max 60W)

USB-C1+USB-C2: 60W+30W (Max 90W)

USB-C1+USB-A: 60W+30W (Max 90W)

USB-C1+USB-C2+USB-A: 60W+ 5V/4.8A (Max. 84W)

Intelligent Power Allocation



Output for UltimatePower 65W GaN USB-C PD Wall Charger Part No. X50065:

USB-C: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/3.25A (Max 65W)

USB-A: 5V/2.4A

USB-C+USB-A: 45W+12W (Max 57W)

Intelligent Power Allocation



Please email us with any questions or feedback you might have about our products to support@ezq.com.

1 (800) 881 9305

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. CAN ICES-3 (B)/NMB-3(B).